

Casambi || receiver | 12-24V | 6A | TW/RGB/RGBW/1..4CH.

ARTICLE NUMBER: 214-205

View this
product in
our
webshop



CASAMBI



21.08.2026 - Disclaimer: information subject to change.



Bluetooth LED controller for constant voltage LED lighting. Suitable for RGB, RGBW, tuneable white and single-colour applications. Operated via the Casambi app or a compatible remote. Maximum output power: 144 W at 24V.

Key product features

- **Number of colour channels:** 4
- **Output voltage (V):** 12 – 24
- **Input voltage (V):** 12 – 24
- **Max. output current (A):** 2
- **Type of control:** Casambi
- **Control type:** Constant voltage
- **Number of zones:** 4

Technical specifications:

Product Name	Casambi receiver 12-24V 6A TW/RGB/RGBW/1..4CH.
Ean	8714984935952
Outer box qty	1st
Model	Dynamic
Housing	Plastic housing
Programmable	Yes
Max. output current	2A
Output voltage	12 - 24V
Suitable for outdoor use	No
Degree of protection (IP)	IP20
Length	72.6mm
Width	30mm
Height	18mm
Number of zones	4
Number of colour channels	4, RGBW

21.08.2026 - Disclaimer: information subject to change.



Suitable for surface mounting	Yes
-------------------------------	-----

Suitable for built-in mounting	No
--------------------------------	----

Input voltage	12 - 24V
---------------	----------

Control method	Casambi
----------------	---------

DIN-rail mounting	No
-------------------	----


Brand	Tronix Lighting
-------	-----------------

Compatible with Casambi	Yes
-------------------------	-----

Control type	Constant voltage
--------------	------------------

Warranty	5 years
----------	---------

21.08.2026 - Disclaimer: information subject to change.



21.08.2026 - Disclaimer: information subject to change.