

Zigbee | driver | 12W | 100~700mA |
max. 42V | NFC

ARTICLE NUMBER: 214-260

View this
product in
our
webshop



24.08.2026 - Disclaimer: information subject to change.



Zigbee 3.0 LED driver for constant current applications up to 12 W. Output current adjustable via NFC. Compatible with Philips Hue, Homey and other smart home platforms.

Key product features

- **Suitable for constant current:** Yes
- **Output voltage (V):** 6 – 42
- **Output current (mA):** 100 – 700
- **Output power (W):** 1 – 12
- **Input voltage (V):** 200 – 240
- **Control protocol:** Zigbee
- **Control type:** Constant current


Technical specifications:

Product Name	Zigbee driver 12W 100~700mA max. 42V NFC
Ean	8714984948365
Outer box qty	1st
Housing	Plastic housing
Model	Static
Output voltage	6 - 42V
Output current	100 - 700mA
Suitable for outdoor use	No
Suitable for DC-voltage (primary side)	Yes
Output power	1 - 12W
Degree of protection (IP)	IP20
Length	135mm
Width	35mm
Height	20mm

24.08.2026 - Disclaimer: information subject to change.

Power consumption	12W
Input voltage	200 - 240V
Frequency input voltage	50 - 60Hz
Overload protection	Yes
Overtemperature protection	Yes
Control method	Zigbee
Short-circuit protected	Yes
Ambient temperature	-25 - 45??C
Driver lifetime	100000h
DIN-rail mounting	No
Brand	Tronix Lighting
Dimmable	Yes
Emergency power supply system	None
Control type	Constant current
Warranty	5 years

24.08.2026 - Disclaimer: information subject to change.



24.08.2026 - Disclaimer: information subject to change.