

Constant current receiver || 4 channels x 700mA

ARTICLE NUMBER: 214-133

View this
product in
our
webshop



24.08.2026 - Disclaimer: information subject to change.



4-channel RF receiver for single-colour LED lighting (700 mA per channel, constant current). Wireless dimming and switching via RF or push-button control. Requires external power supply (12–36V DC). Can be paired with up to 8 remote controls.

Key product features

- **Type of control:** RF
- **Number of colour channels:** 1
- **Input voltage (V):** 12–36
- **Max. output current (A):** 0.7
- **Control type:** Constant current

Technical specifications:

Product Name	Constant current receiver 4 channels x 700mA
Ean	8714984910423
Outer box qty	1st
Model	Dynamic
Housing	Plastic housing
Programmable	No
Max. output current	0.7A
Output voltage	12 - 36V
Suitable for outdoor use	No
Degree of protection (IP)	IP20
Length	178mm
Width	45mm
Height	19mm
Number of zones	1
Number of colour channels	1, Single Colour
Suitable for surface mounting	Yes

24.08.2026 - Disclaimer: information subject to change.



Suitable for built-in mounting	No
Input voltage	12 - 36V
Control method	RF
DIN-rail mounting	No
Brand	Tronix Lighting
Compatible with Casambi	No
Control type	Constant current
Warranty	5 years

24.08.2026 - Disclaimer: information subject to change.